



TEP-1560-IMX6 MODULAR HMI PRODUCT MANUAL
(TEP-1560-IMX6)

VER. 1.01

February 25, 2019

REVISION HISTORY

Revision	Date	Originator	Notes
1.00	September 12, 2018	TechNexion	First public release
1.01	February 25, 2019	TechNexion	Ordering table update

TABLE OF CONTENTS

1. Introduction	5
1.1. General Care and Maintenance	5
2. TEP-1560-IMX6 Product Overview	6
2.1. Functional Block Diagram	6
2.2. Dimensions	7
2.3. Device Cut-out Dimensions For Mounting Though a Panel	8
2.4. External Connectors	9
2.5. Internal Board Connectors	10
2.5.1. Galvanic Isolated (TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx)	10
2.5.2. Non-Galvanic Isolated (TEP1560-IMX6x-Rxx-Exx-Lxxx-XS20-xxx-xxxx)	11
3. External Connectors	12
3.1. LED Light Indicator	12
3.2. Micro-SIM Card Slot	12
3.3. MicroSD Card Slot	12
3.4. USB OTG (Type-C) Connector	13
3.5. USB Host Connector	13
3.6. HDMI (High Definition Multi-Media Interface) Connector	13
3.7. VGA (15-pin D-SUB) Connector	13
3.8. Audio Connectors	14
3.9. S1 Button	14
3.10. RST Button	14
3.11. Power Input Connector	14
3.12. Gigabit Ethernet Interface	15
3.13. Antenna Holes	15
3.14. Galvanic Isolated Connectors (TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx) (optional)	16
3.14.1. Galvanic Isolated Digital I/O Connectors (GPIO1/GPIO2) (optional)	16
3.14.2. Galvanic Isolated Serial Port (RS-XXX) (optional)	18
3.14.3. Galvanic Isolated CAN Bus Connector (CANBus) (optional)	20
3.15. Non-Galvanic Isolated Connectors (TEP1560-IMX6x-Rxx-Exx-Lxxx-XS20-xxx-xxxx) (optional) ..	21
3.15.1. Non-Galvanic Isolated Digital I/O Connectors (GPIO1/GPIO2) (optional)	21
3.15.2. Non-Galvanic Isolated Serial Port (RS-XXX) (optional)	22
3.15.3. Non-Galvanic Isolated CAN Bus Connector (CANBus) (optional)	23
4. Internal Connectors and Expansion Options	24
4.1. Mini-PCIe Connectors	24
4.2. Mini-SIM Card slot	24
4.3. M.2 KEY-B Slots	25

4.4. SW2 Default Boot Mode Switch	25
4.5. SWITCH1 Boot Mode DIP Switch	25
4.6. RTC Battery Connector	25
4.7. Internal Stereo Speaker Connectors	26
5. Mounting.....	27
5.1. VESA Mounting	27
5.2. Rear Mounting and Mounting Clips Installation.....	28
5.3. Surface Mounting and O-ring Installation	29
6. Ordering Information	30
6.1. Custom Part Number Rule	30
6.2. Standard Package Contents	31
7. Important Notice	32
8. Disclaimer	33

1. Introduction

1.1. General Care and Maintenance

Your device is a product of superior design and craftsmanship and should be treated with care.

The following suggestions will help you.

- Keep the device dry. Precipitation, humidity, and all types of liquids or moisture can contain minerals that will corrode electronic circuits. If your device does get wet, allow it to dry completely.
- Do not use or store the device in dusty or dirty areas. Its parts and electronic components can be damaged.
- Do not store the device in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.
- Do not store the device in cold areas. When the device returns to its normal temperature, moisture can form inside the device and damage electronic circuit boards.
- Do not open the device while power is on. Otherwise electrical shock may result.
- Do not drop, knock, or shake the device. Rough handling can break internal circuit boards and fine mechanics.
- Do not use harsh chemicals, cleaning solvents, or strong detergents to clean the device.
- Do not paint the device. Paint can clog the parts and prevent proper operation.
- Unauthorized modifications or attachments could damage the device and may violate regulations governing radio devices.

These suggestions apply equally to your device, battery, charger, or any enhancement. If any device is not working properly, take it to the nearest authorized service facility for service.

Regulatory information




Disposal of Waste Equipment by Users in Private Household in the European Union
This symbol on the product or on its packaging indicates that this product must not be disposed of with your other household waste. Instead, it is your responsibility to dispose of your waste equipment by handing it over to a designated collection point for the recycling of waste electrical and electronic equipment. The separate collection and recycling of your waste equipment at the time of disposal will help to conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment. For more information about where you can drop off your waste equipment for recycling, please contact your local city office, your household waste disposal service or the shop where you purchased the product.



We hereby declare that the product is in compliance with the essential requirements and other relevant provisions of European Directive 2014/53/EU (Directive on the harmonisation of the laws of the Member States relating to the making available on the market of radio equipment and repealing Directive 1999/5/EC).


2. TEP-1560-IMX6 Product Overview

2.1. Functional Block Diagram




2.2. Dimensions

The following figure shows the TEP-1560-IMX6 dimensions (unit: mm):



2.3. Device Cut-out Dimensions For Mounting Though a Panel

The TEP-1560-IMX6 can be mounted on the front or the back of the panel. In order to mount it from the front, a nominal rectangular cutout must be made in the panel. The following drawing shows the dimensions of the cut-out area (unit: mm):



2.4. External Connectors

The TEP-1560-IMX6 has a number of external connectors.
Bottom view:



External Connectors:


No.	Description	No.	Description
1	LED Light indicator	12	3.5mm jack Line in
2	Micro-SIM card slot	13	3.5mm jack Mic in
3	MicroSD card slot	14	S1 Boot Select button
4	USB OTG (Type-C) connector	15	Reset button
5	USB Host connector	16	Power Input connector
6	USB Host connector	17	LAN RJ45 connector
7	USB Host connector	18	GPIO1 connector (optional)
8	USB Host connector	19	GPIO2 connector (optional)
9	HDMI connector	20	RS-XXX (Serial Port) connector (optional)
10	VGA (15-pin D-SUB) connector	21	CAN Bus connector (optional)
11	3.5mm jack Line out		

2.5. Internal Board Connectors

The TEP-1560-IMX6 has several connectors, switches and internal expansion options.

2.5.1. Galvanic Isolated (TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx)

Rear view (opened device) with the galvanic isolated I/O Expansion module:




Internal Connectors and Switches:

No.	Description	No.	Description
A	mini-PCIe connector (PCIe + USB)	F	Mini-SIM card slot
B	mini-PCIe connector (USB)	G	M.2 KEY-B slot (SATA + USB)
C	SW2 Default Boot mode switch	H	SWITCH1 Boot mode DIP switch
D	M.2 KEY-B slot (USB)	I	Internal R speaker connector
E	RTC Battery connector	J	Internal L speaker connector

NOTE: Three additional switches are available on the rear side of the galvanic isolated I/O Expansion module (TXR-I2-GS2-GC2-GG8) (optional). Please see section [3.14. Galvanic Isolated Connectors \(TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx\) \(optional\)](#) for more details.

2.5.2. Non-Galvanic Isolated (TEP1560-IMX6x-Rxx-Exx-Lxxx-**XS20**-xxx-xxxx)

Rear view (opened device) with the non-galvanic isolated I/O Expansion module:



Internal Connectors and Switches:

No.	Description	No.	Description
A	mini-PCIe connector (PCIe + USB)	F	Mini-SIM card slot
B	mini-PCIe connector (USB)	G	M.2 KEY-B slot (SATA + USB)
C	SW2 Default Boot mode switch	H	SWITCH1 Boot mode DIP switch
D	M.2 KEY-B slot (USB)	I	Internal R speaker connector
E	RTC Battery connector	J	Internal L speaker connector

NOTE: One additional switch is available on the rear side of the non-galvanic isolated I/O Expansion module (TXR-I2-S2-C2-G8) (optional). Please see section [3.15. Non-Galvanic Isolated Connectors \(TEP1560-IMX6x-Rxx-Exx-Lxxx-XS20-xxx-xxxx\) \(optional\)](#) for more details.

3. External Connectors

3.1. LED Light Indicator

The TEP-1560-IMX6 has one programmable LED Light indicator.

LED #	Color	GPIO Kernel	GPIO Bank/IO
1	Green	9	1_9

3.2. Micro-SIM Card Slot

The TEP-1560-IMX6 features an external Micro-SIM card slot for use by 3G/4G/LTE wireless module.

NOTE: This card slot can be only used by a mini-PCIe 3G/4G/LTE module installed into the MPCIE1 connector. The MPCIE1 connector can be found at location “A” in chapter [4. Internal Connectors and Expansion Options](#) of this manual. No mini-PCIe 3G/4G LTE module is included in this device (must be purchased separately, not sold by TechNexion).

3.3. MicroSD Card Slot

The TEP-1560-IMX6 features a standard microSD card slot which is connected to the NXP i.MX6 integrated “Ultra Secured Digital Host Controller” (uSDHC).


The following main features are supported by uSDHC:

- Compatible with the MMC System Specification version 4.2/4.3/4.4/4.41/5.0.
- Conforms to the SD Host Controller Standard Specification version 3.0.
- Compatible with the SD Memory Card Specification version 3.0 and supports the “Extended Capacity SD Memory Card”.
- Compatible with the SDIO Card Specification version 3.0.
- Supports 1-bit / 4-bit SD and SDIO modes

The MMC/SD/SDIO host controller can support a single MMC / SD / SDIO card or device.

3.4. USB OTG (Type-C) Connector

The TEP-1560-IMX6 has one USB Type-C connector (USB 2.0 signals only) that can be used to connect a host computer to the unit for programming and update purposes.



Pin #	Signal	Description	Pin #	Signal	Description
A1	GND	Ground	B1	GND	Ground
A2	NC		B2	NC	
A3	NC		B3	NC	
A4	VBUS	5V Universal Serial Bus Power	B4	VBUSD	5V Universal Serial Bus Power
A5	CC1	OTG detection signal	B5	CC2D	OTG detection signal
A6	USB_D+	USB differential pair signal port 1	B6	USB_D+	USB differential pair signal port 2
A7	USB_D-		B7	USB_D-	
A8	NC		B8	NC	
A9	VBUS	5V Universal Serial Bus Power	B9	VBUSD	5V Universal Serial Bus Power
A10	NC		B10	NC	
A11	NC		B11	NC	
A12	GND	Ground	B12	GND	Ground

3.5. USB Host Connector

The TEP-1560-IMX6 has four USB Host connectors (USB 2.0 signals only) to connect to a USB peripheral such as a keyboard, mouse, USB storage device or USB hub.

3.6. HDMI (High Definition Multi-Media Interface) Connector

The HDMI interface available on the TEP-1560-IMX6 is based on the “HDMI transmitter” & “HDMI 3D TX PHY” integrated into the NXP i.MX6 processor and can be configured to support a secondary display.

The HDMI supports the following standards & features:

- High-Definition Multimedia Interface Specification, Version 1.4a
- Digital Visual Interface, Revision 1.0
- HDMI Compliance Test Specification, Version 1.4a
- Support for up to 720p at 100Hz and 720i at 200Hz or 1080p at 60Hz and 1080i/720i at 120Hz HDTV display resolutions and up to QXGA graphic display resolutions.
- Support for 4k x 2k and 3D video formats
- Support for up to 16-bit Deep Color modes

3.7. VGA (15-pin D-SUB) Connector

The VGA interface available on the TEP-1560-IMX6 can be configured to support a secondary display.

3.8. Audio Connectors

The TEP-1560-IMX6 has three external 3.5mm stereo audio jacks.

Color Code	Signal	Description
Green	L/R Line out	Audio output
Blue	L/R Line in	Audio input
Pink	Mic in	Microphone input

3.9. S1 Button

The TEP-1560-IMX6 by default boots the unit from internal flash storage (eMMC). By pressing the “S1” button before applying power to the unit and keeping the button pressed for 10 seconds, the unit will boot from an alternative boot media, such as a microSD card. The primary and alternative boot media are determined by internal DIP switch settings. Please see sections [4.4. SW2 Default Boot Mode Switch](#) and [4.5. SWITCH1 Boot Mode DIP Switch](#) for more details.


3.10. RST Button

The TEP-1560-IMX6 features a “RST” button for system reset.

3.11. Power Input Connector

The TEP-1560-IMX6 can be powered either over the DC INPUT connector or PoE (optional) over the RJ45 LAN port.

NOTE: Do not power the unit by DC input when you apply power over the Power over Ethernet (RJ45)!




Pin #	Signal	Description
1	GND	Ground
2	VCC	DC Voltage input (12V/24V/8~36VDC)

Header on TEP-1560-IMX6: Molex 43045-0200 (2-pin Micro-Fit 3.0).

Cable receptacle: Molex 43025-0200 (2-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.12. Gigabit Ethernet Interface

The TEP-1560-IMX6 by default comes with a single Gigabit Ethernet RJ45 connector. This connector can support 802.3at Power over Ethernet functionality if configured with the PoE power option (TEP1560-IMX6x-Rxx-Exx-**LPOE**-Xxxx-xxx-xxxx) by connecting it to an 802.3at compliant PoE switch or power injector.



Pin #	1000 Mbps	100 Mbps	10 Mbps
1	MDI0+	Transmit Data+	Transmit Data+
2	MDI0-	Transmit Data-	Transmit Data-
3	MDI1+	Receive Data+	Receive Data+
4	MDI2+		
5	MDI2-		
6	MDI1-	Receive Data-	Receive Data-
7	MDI3+		
8	MDI3-		


3.13. Antenna Holes

There are six antenna holes available (each two on the left side, on the right side and on the top side). They come fitted with breakaway metal tabs. In order to utilize them, the tabs must be removed by carefully using pincers or pliers.

3.14. Galvanic Isolated Connectors (TEP1560-IMX6x-Rxx-Exx-Lxxx-**XG20**-xxx-xxxx) (optional)

This product is available with four optional connectors: GPIO1, GPIO2, RS-XXX and CAN Bus that can be ordered in either galvanic isolated or non-galvanic isolated versions. The TEP1560-IMX6x-Rxx-Exx-Lxxx-**XG20**-xxx-xxxx has four optional galvanic isolated connectors: GPIO1, GPIO2, RS-XXX and CAN Bus.


Rear view of the galvanic isolated I/O Expansion module (TXR-I2-GS2-GC2-GG8):



No.	Description	No.	Description
A	SW1 DIP switch	C	SW2 Terminator Resistor DIP switch
B	SW3 Terminator Resistor DIP switch		

3.14.1. Galvanic Isolated Digital I/O Connectors (GPIO1/GPIO2) (optional)

The galvanic isolated GPIO Expansion headers have the following pinout:



GPIO1:

Pin #	Signal	Description	Voltage			Current Max.	GPIO Kernel	GPIO Bank/IO
			Min.	Typ.	Max.			
1	GPIO1A	DIG_IN1			6V	1A	161	6_1
2	GPIO1B	DIG_IN2			6V	1A	42	2_10
3	GND_DIO	Ground for digital I/O						
4	GND	Common Ground						
5	GPIO1C	DIG_OUT5			16V	1.7A	1	1_1
6	GPIO1D	DIG_OUT6			16V	1.7A	102	4_6
7	VCC_DIO	Supply input for digital I/O			16V			
8	VCC	Supply output		12V				

GPIO2:

Pin #	Signal	Description	Voltage			Current Max.	GPIO Kernel	GPIO Bank/IO
			Min.	Typ.	Max.			
1	GPIO2A	DIG_IN1			6V	1A	165	6_5
2	GPIO2B	DIG_IN2			6V	1A	164	6_4
3	GND_DIO	Ground for digital I/O						
4	GND	Common Ground						
5	GPIO2C	DIG_OUT5			16V	1.7A	162	6_2
6	GPIO2D	DIG_OUT6			16V	1.7A	163	6_3
7	VCC_DIO	Supply input for digital I/O			16V			
8	VCC	Supply output		12V				

Header on TEP-1560-IMX6: Molex 43045-0800 (8-pin Micro-Fit 3.0).

Cable receptacle: Molex 43025-0800 (8-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.14.2. Galvanic Isolated Serial Port (RS-XXX) (optional)


The dual 4-wire galvanic isolated serial port can be configured as follows: the primary serial port can only be used as a standard RS-232. The secondary port can be configured either as RS-232, or RS-422 or RS-485. This serial port is set by default as RS-232. Setting the TEP-1560-IMX6 in other mode will require to open the device, disconnect the TEP I/O Expansion board and adjust the internal SW1 DIP and SW3 Terminator Resistor DIP switch settings on the TEP I/O Expansion board. The SW1 DIP switch can be found at location “A” and SW3 DIP switch at location “B” in chapter [3.14. Galvanic Isolated Connectors \(TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx\) \(optional\)](#) of this manual.

SW1:

Pin #	RS-232 (default)	RS-422	RS-485
1-8	ON	OFF	OFF
2-7	OFF	ON	OFF
3-6	OFF	OFF	ON
4-5	-	-	-

SW3:

Pin #	ON	OFF
1-8	Enable RS-485 Terminator Resistor	Disable RS-485 Terminator Resistor
2-7	Enable RS-422 Terminator Resistor	Disable RS-422 Terminator Resistor
3-6	-	-
4-5	-	-



RS-232 + RS-232 (default setup):

Pin #	Signal	Description	Device
1	GND	Ground	
2	SERIAL1A_TXD	Port#1A Transmit data (output)	ttymxc0
3	SERIAL1A_RXD	Port#1A Receive data (input)	ttymxc0
4	SERIAL1A_RTS	Port#1A Request-to-send (output)	ttymxc0
5	SERIAL1A_CTS	Port#1A Clear-to-send (input)	ttymxc0
6	GND	Ground	
7	SERIAL1B_TXD	Port#1B Transmit data (output)	ttymxc1
8	SERIAL1B_RXD	Port#1B Receive data (input)	ttymxc1
9	SERIAL1B_RTS	Port#1B Request-to-send (output)	ttymxc1
10	SERIAL1B_CTS	Port#1B Clear-to-send (input)	ttymxc1

RS-232 + RS-422:

Pin #	Signal	Description	Device
1~5	SERIAL1A	Identical as above	ttymxc0
6	GND	Ground	
7	SERIAL1B_TXD+	RS-422 Transmit positive data signal (output)	ttymxc1
8	SERIAL1B_RXD-	RS-422 Receive negative data signal (input)	ttymxc1
9	SERIAL1B_RXD+	RS-422 Receive positive data signal (input)	ttymxc1
10	SERIAL1B_TXD-	RS-422 Transmit negative data signal (output)	ttymxc1

RS-232 + RS-485:

Pin #	Signal	Description	Device
1~5	SERIAL1A	Identical as above	ttymxc0
6	GND	Ground	
7	SERIAL1B+	RS-485 positive data signal	ttymxc1
8	NC		
9	NC		
10	SERIAL1B-	RS-485 negative data signal	ttymxc1

NOTE: SERIAL1A port can act by default as a serial debug console.

Header on TEP-1560-IMX6: Molex 43045-1000 (10-pin Micro-Fit 3.0).


Cable receptacle: Molex 43025-1000 (10-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.14.3. Galvanic Isolated CAN Bus Connector (CANBus) (optional)

The galvanic isolated CAN Bus interfaces can be configured as follows: enabling or disabling of CAN Bus terminator resistor will require to open the device, disconnect the TEP I/O Expansion board and adjust the internal SW2 Terminator Resistor DIP switch settings on the TEP I/O Expansion board. The SW2 DIP switch can be found at location “C” in chapter [3.14. Galvanic Isolated Connectors \(TEP1560-IMX6x-Rxx-Exx-Lxxx-XG20-xxx-xxxx\) \(optional\)](#) of this manual.

SW2:

Pin #	ON	OFF (default)
1-8	Enable CAN1A Terminator Resistor	Disable CAN1A Terminator Resistor
2-7	Enable CAN1A Terminator Resistor	Disable CAN1A Terminator Resistor
3-6	Enable CAN1B Terminator Resistor	Disable CAN1B Terminator Resistor
4-5	Enable CAN1B Terminator Resistor	Disable CAN1B Terminator Resistor



CANBus:

Pin #	Signal	Description	Interface
1	GND_CAN	Ground for CAN	
2	CAN1A_TERM_N	To enable CAN1A Termination, bridge with CAN1A_N	can0
3	CAN1A_P	CAN Bus 1A high (-24~+24V)	can0
4	CAN1A_N	CAN Bus 1A low (-24~+24V)	can0
5	CAN1A_TERM_P	To enable CAN1A Termination, bridge with CAN1A_P	can0
6	NC		
7	GND_CAN	Ground for CAN	
8	CAN1B_TERM_N	To enable CAN1B Termination, bridge with CAN1B_N	can1
9	CAN1B_P	CAN Bus 1B high (-24~+24V)	can1
10	CAN1B_N	CAN Bus 1B low (-24~+24V)	can1
11	CAN1B_TERM_P	To enable CAN1B Termination, bridge with CAN1B_P	can1
12	NC		


Header on TEP-1560-IMX6: Molex 43045-1200 (12-pin Micro-Fit 3.0).

Cable receptacle: Molex 43025-1200 (12-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.15. Non-Galvanic Isolated Connectors (TEP1560-IMX6x-Rxx-Exx-Lxxx-**XS20**-xxx-xxxx) (optional)

This product is available with four optional connectors: GPIO1, GPIO2, RS-XXX and CAN Bus that can be ordered in either galvanic isolated or non-galvanic isolated versions. The TEP1560-IMX6x-Rxx-Exx-Lxxx-**XS20**-xxx-xxxx has four optional non-galvanic isolated connectors: GPIO1, GPIO2, RS-XXX and CAN Bus.


Rear view of the non-galvanic isolated I/O Expansion module (TXR-I2-S2-C2-G8):



No.	Description	No.	Description
A	SW1 Terminator Resistor DIP switch		

3.15.1. Non-Galvanic Isolated Digital I/O Connectors (GPIO1/GPIO2) (optional)

The non-galvanic isolated GPIO Expansion headers have the following pinout:



GPIO1:

Pin #	Signal	Description	Voltage			Current Max.	GPIO Kernel	GPIO Bank/IO
			Min.	Typ.	Max.			
1	GPIO1A	DIG_IN1/OUT1	1.65V	3.3V	3.6V	0.33mA	161	6_1
2	GPIO1B	DIG_IN2/OUT2	1.65V	3.3V	3.6V	0.33mA	42	2_10
3	NC							
4	GND	Common Ground						
5	GPIO1C	DIG_IN5/OUT5	1.65V	3.3V	3.6V	0.33mA	1	1_1
6	GPIO1D	DIG_IN5/OUT6	1.65V	3.3V	3.6V	0.33mA	102	4_6
7	NC							
8	VCC	Supply output		12V				

GPIO2:


Pin #	Signal	Description	Voltage			Current Max.	GPIO Kernel	GPIO Bank/IO
			Min.	Typ.	Max.			
1	GPIO2A	DIG_IN1/OUT1	1.65V	3.3V	3.6V	0.33mA	164	6_4
2	GPIO2B	DIG_IN2/OUT2	1.65V	3.3V	3.6V	0.33mA	165	6_5
3	NC							
4	GND	Common Ground						
5	GPIO2C	DIG_IN5/OUT5	1.65V	3.3V	3.6V	0.33mA	162	6_2
6	GPIO2D	DIG_IN5/OUT6	1.65V	3.3V	3.6V	0.33mA	163	6_3
7	NC							
8	VCC	Supply output		12V				

Header on TEP-1560-IMX6: Molex 43045-0800 (8-pin Micro-Fit 3.0).

Cable receptacle: Molex 43025-0800 (8-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.15.2. Non-Galvanic Isolated Serial Port (RS-XXX) (optional)

The dual 4-wire non-galvanic isolated serial port are configured as follows: the primary and the secondary serial port can only be used as a standard RS-232.



RS-232 + RS-232:

Pin #	Signal	Description	Device
1	GND	Ground	
2	SERIAL1A_TXD	Port#1A Transmit data (output)	ttymxc0
3	SERIAL1A_RXD	Port#1A Receive data (input)	ttymxc0
4	SERIAL1A_RTS	Port#1A Request-to-send (output)	ttymxc0
5	SERIAL1A_CTS	Port#1A Clear-to-send (input)	ttymxc0
6	GND	Ground	
7	SERIAL1B_TXD	Port#1B Transmit data (output)	ttymxc1
8	SERIAL1B_RXD	Port#1B Receive data (input)	ttymxc1
9	SERIAL1B_RTS	Port#1B Request-to-send (output)	ttymxc1
10	SERIAL1B_CTS	Port#1B Clear-to-send (input)	ttymxc1

NOTE: SERIAL1A port can act by default as a serial debug console.

Header on TEP-1560-IMX6: Molex 43045-1000 (10-pin Micro-Fit 3.0).


Cable receptacle: Molex 43025-1000 (10-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

3.15.3. Non-Galvanic Isolated CAN Bus Connector (CANBus) (optional)

The non-galvanic isolated CAN Bus interfaces can be configured as follows: enabling or disabling of CAN Bus terminator resistor will require to open the device, disconnect the TEP I/O Expansion board and adjust the internal SW1 Terminator Resistor DIP switch settings on the TEP I/O Expansion board. The SW1 DIP switch can be found at location “A” in chapter [3.15. Non-Galvanic Isolated Connectors \(TEP1560-IMX6x-Rxx-Exx-Lxxx-XS20-xxx-xxxx\) \(optional\)](#) of this manual.

SW1:

Pin #	ON	OFF (default)
1-8	Enable CAN1A Terminator Resistor	Disable CAN1A Terminator Resistor
2-7	Enable CAN1A Terminator Resistor	Disable CAN1A Terminator Resistor
3-6	Enable CAN1B Terminator Resistor	Disable CAN1B Terminator Resistor
4-5	Enable CAN1B Terminator Resistor	Disable CAN1B Terminator Resistor



CANBus


Pin #	Signal	Description	Interface
1	GND_CAN	Ground for CAN	
2	CAN1A_TERM_N	To enable CAN1A Termination, bridge with CAN1A_N	can0
3	CAN1A_P	CAN Bus 1A high (-24~+24V)	can0
4	CAN1A_N	CAN Bus 1A low (-24~+24V)	can0
5	CAN1A_TERM_P	To enable CAN1A Termination, bridge with CAN1A_P	can0
6	NC		
7	GND_CAN	Ground for CAN	
8	CAN1B_TERM_N	To enable CAN1B Termination, bridge with CAN1B_N	can1
9	CAN1B_P	CAN Bus 1B high (-24~+24V)	can1
10	CAN1B_N	CAN Bus 1B low (-24~+24V)	can1
11	CAN1B_TERM_P	To enable CAN1B Termination, bridge with CAN1B_P	can1
12	NC		

Header on TEP-1560-IMX6: Molex 43045-1200 (12-pin Micro-Fit 3.0).

Cable receptacle: Molex 43025-1200 (12-pin Micro-Fit 3.0) plug with crimp contact Molex 43030-0007.

4. Internal Connectors and Expansion Options

Rear view (opened device) with the I/O Expansion module:



Internal Connectors and Switches:

No.	Description	No.	Description
A	mini-PCIe connector (PCIe + USB)	F	Mini-SIM card slot
B	mini-PCIe connector (USB)	G	M.2 KEY-B slot (SATA + USB)
C	SW2 Default Boot mode switch	H	SWITCH1 Boot mode DIP switch
D	M.2 KEY-B slot (USB)	I	Internal R speaker connector
E	RTC Battery connector	J	Internal L speaker connector

NOTE: Items marked with * are accessible only after removing the I/O Expansion module.

4.1. Mini-PCIe Connectors

The TEP-1560-IMX6 has two internal mini-PCIe connectors for full or half size cards: MPCIE1 and MPCIE2 (Marked A and B respectively). MPCIE1 connector supports PCIe and USB signals. On the other hand, MPCIE2 connector supports USB signals only. Mini-PCIe full size (30 x 50.95 mm) or half size (30 x 26.8 mm) cards are supported.

4.2. Mini-SIM Card slot

The TEP-1560-IMX6 features an internal Mini-SIM card slot for use by 3G/4G/LTE wireless module (Marked G).

NOTE: This card slot can be only used by a mini-PCIe 3G/4G/LTE module installed into the MPCIE2 connector (Marked B). No mini-PCIe 3G/4G LTE module is included in this device (must be purchased separately, not sold by TechNexion).

4.3. M.2 KEY-B Slots

The TEP-1560-IMX6 has two internal M.2 connectors: M2-1 and M2-2 (Marked H and D respectively). M2-1 connector supports either SATA and USB signals (TEP1560-**IMX6Q**-Rxx-Exx-Lxxx-xxxx-xxx-xxxx) or USB signals only (TEP1560-**IMX6S**-Rxx-Exx-Lxxx-xxxx-xxx-xxxx or TEP1560-**IMX6U**-Rxx-Exx-Lxxx-xxxx-xxx-xxxx). On the other hand, M2-2 connector supports USB signals only. M.2 cards in the M.2 KEY-B 2242 (22 x 42 mm) form factor are supported.

4.4. SW2 Default Boot Mode Switch

The TEP-1560-IMX6 has an internal SW2 Default Boot Mode switch (Marked C).

Pin #	eMMC (default)	microSD	SATA
1-8	ON	ON	OFF
2-7	ON	OFF	ON
3-6	ON	OFF	-
4-5	ON	OFF	-

4.5. SWITCH1 Boot Mode DIP Switch


The TEP-1560-IMX6 has an internal SWITCH1 Default Boot Mode DIP switch for S1 boot select button (Marked I).

Pin #	eMMC	microSD (default)	SATA*
1-16	OFF	ON	OFF
2-15	OFF	ON	-
3-14	ON	OFF	ON
4-13	ON	OFF	-
5-12	ON	OFF	-
6-11	OFF	OFF	OFF
7-10	ON	ON	OFF
8-9	OFF	OFF	OFF

NOTE: SATA boot mode is available on the TEP1560-**IMX6Q**-Rxx-Exx-Lxxx-xxxx-xxx-xxxx only.

4.6. RTC Battery Connector

The TEP-1560-IMX6 features an internal RTC backup battery connector (Marked E).




Pin #	Signal	Description
1	RTC_VCC	3V (connect to standard CR2032 battery)
2	GND	Ground

Header on TEP-1560-IMX6: Molex 53047-0210 (1.25mm Pitch PicoBlade Wire-to-Board Header).
 Cable receptacle: Molex 051021-8602 (1.25mm Pitch PicoBlade Wire-to-Wire and Wire-to-Board Housing) plug with crimp contact Molex 50058-8000.
 Battery P/N: KTS BCR2032H14.0AM1XB.

4.7. Internal Stereo Speaker Connectors

The TEP-1560-IMX6 has two internal stereo speaker connectors to connect to two optional LEFT and RIGHT speakers (Marked K and J respectively). The signal is pre-amplified with a 2W Texas Instruments TPA2012D2 Class-D stereo audio amplifier.



LEFT Speaker connector (Marked K).

Pin #	Signal	Description
1	S_OUTL+	LEFT Speaker Positive Signal
2	S_OUTL-	LEFT Speaker Analog Ground Signal

RIGHT Speaker connector (Marked J).

Pin #	Signal	Description
1	S_OUTR+	RIGHT Speaker Positive Signal
2	S_OUTR-	RIGHT Speaker Analog Ground Signal

Header on TEP-1560-IMX6: Molex 53047-0210 (1.25mm Pitch PicoBlade Wire-to-Board Header).

Cable receptacle: Molex 051021-8602 (1.25mm Pitch PicoBlade Wire-to-Wire and Wire-to-Board Housing) plug with crimp contact Molex 50058-8000.

5. Mounting

This section describes the mounting procedures for the TEP-1560-IMX6. The material in area of the mounting must provide sufficient strength for safe mounting of this device.


5.1. VESA Mounting

The TEP-1560-IMX6 is compatible with the VESA MIS-D Standard 100*100mm hole pattern. There are 4 VESA MIS-D (M4) mounting holes on the rear side of the device. M4 screw holes are a depth of 6mm.



5.2. Rear Mounting and Mounting Clips Installation

There are 14 mounting clips required for rear mounting.




Please follow the steps below to secure the clips. Prepare mounting hook, post and screw (M3) (Step 1). Locate all removable tabs on the rear side of your device and use pincers or pliers to remove the tabs (Step 2-3). Press the mounting clip into the holes at an angle and slowly straighten it (Step 4-5). Then tighten the screw to the surface (Step 6). Repeat the steps for all clips required to secure your device.



5.3. Surface Mounting and O-ring Installation

There are 16 mounting holes (M4) on the rear side of the device required for surface mounting. M4 screws with at least 6mm head-to-tip length are required to secure this device



Please follow the steps below to properly install the waterproof rubber O-ring. Prepare your device and O-ring (Step 1-2). First, align the O-ring with the groove and press the O-ring into the corners of the O-ring groove (Step 3-4). Then, press it into the center (Step 5). Finally, stretch it uniformly around the O-ring groove (Step 6). Do not pull from one side, and make sure that you stretch it as little as possible.



6. Ordering Information

The TEP-1560-IMX6 is available in several configurations. Please contact your TechNexion sales contact window or distributor for options and availability details.

6.1. Custom Part Number Rule

The TEP-1560-IMX6 can be ordered in custom tailored configuration to meet special application requirements and conditions according to the following custom part number creation rules. Custom part numbers carry minimum order quantities (MOQ). Please connect with your TechNexion distributor or account manager for conditions and availability. Part number format:

TEP1560-IMX6x-Rxx-Exx-Lxxx-Xxxx-xxx-xxxx-xxxx

Interface	Code	Description
Processor	IMX6S	NXP i.MX6Solo
	IMX6U	NXP i.MX6DualLite
	IMX6Q	NXP i.MX6Quad
Memory	R05	512MB DDR3
	R10	1GB DDR3
	R20	2GB DDR3
Storage	E04	eMMC 4GB
	E08	eMMC 8GB
	EXX	eMMC other capacity
Power Expansion	L112	TXR-P1-12V-LAN1 (12V 3A)
	L130	TXR-P1-1030V-LAN1 (8-36V 5A)
	LPOE	TXR-P1-12V-POE1 (12V 3A) or (PoE 802.3at)
I/O Expansion	-	-
	XS20	2x RS-232 + 2x CAN + 8x GPIO
	XG20	2x RS-232 + 2x CAN + 8x GPIO (Galvanic Isolated)
Internal Speaker	-	-
	SPK	2x 2W/8Ω Stereo Speaker
Wi-Fi / Bluetooth	-	-
	9377	Qualcomm QCA9377 802.11a/b/g/n/ac (2.4 + 5GHz) + Bluetooth 5
Custom ID	XXXX	Custom Part number ID for customized software loader and special component (BOM)

6.2. Standard Package Contents



Item	Partnumber	Description
1	TEP-1560-IMX6	15.6 inch PoE HMI PCAP touch system with NXP i.MX6
2	Accessoires	14x mounting hooks
		14x long screws (M3)
		14x mounting posts
		2x hexagonal bolt
		2x mini-PCIe screw (M2)
		2x screw (M3)
		2x plastic washer
		1x rubber O-ring
		1x DC power latch cable (2-pin Micro-Fit 3.0)

NOTE: Pack contents might vary depending on your ordered configuration.

7. Important Notice

TechNexion reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TechNexion terms and conditions of sale supplied at the time of order acknowledgment.

TechNexion warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TechNexion standard warranty. Testing and other quality control techniques are used to the extent TechNexion deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TechNexion assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TechNexion components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TechNexion does not warrant or represent that any license, either express or implied, is granted under any TechNexion patent right, copyright, mask work right, or other TechNexion intellectual property right relating to any combination, machine, or process in which TechNexion products or services are used. Information published by TechNexion regarding third-party products or services does not constitute a license from TechNexion to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TechNexion under the patents or other intellectual property of TechNexion.

TechNexion products are not authorized for use in safety-critical applications (such as life support) where a failure of the TechNexion product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TechNexion products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TechNexion. Further, Buyers must fully indemnify TechNexion and its representatives against any damages arising out of the use of TechNexion products in such safety-critical applications.

TechNexion products are neither designed nor intended for use in military/aerospace applications or environments unless the TechNexion products are specifically designated by TechNexion as military grade or "enhanced plastic." Only products designated by TechNexion as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TechNexion products which TechNexion has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TechNexion products are neither designed nor intended for use in automotive applications or environments unless the specific TechNexion products are designated by TechNexion as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TechNexion will not be responsible for any failure to meet such requirements.

8. Disclaimer

© 2001-2019 TechNexion Ltd.

All Rights Reserved. No part of this document may be photocopied, reproduced, stored in a retrieval system, or transmitted, in any form or by any means whether, electronic, mechanical, or otherwise without the prior written permission of TechNexion Ltd.

No warranty of accuracy is given concerning the contents of the information contained in this publication. To the extent permitted by law no liability (including liability to any person by reason of negligence) will be accepted by TechNexion Ltd., its subsidiaries or employees for any direct or indirect loss or damage caused by omissions from or inaccuracies in this document.

TechNexion Ltd. reserves the right to change details in this publication without notice.

Product and company names herein may be the trademarks of their respective owners.

TechNexion Ltd.
16F-5, No. 736, Zhongzheng Road,
ZhongHe District, 23511, New Taipei City, Taiwan
Phone : +886-2-82273585
Fax : +886-2-82273590
E-mail : sales@technexion.com
Web : <https://www.technexion.com/>